



8 Channel Stereo Mixer

## MR-8022FX



MR-8022FX

### Features:

- 8 Mono Input Channels with silver plated XLRs and balanced Line Inputs
- Ultra-low noise discrete Mic Preamps with +48 V Phantom Power
- Ultra-musical 3-band EQ on all channels
- Peak LEDs all Mono Channels
- 1 Aux Send per channel for external effects
- Built in digital effect (16 DSP)
- Highly accurate 10 segment Bargraph Meters
- 1 Stereo master output and 2 Group output

SPECIFICATIONS	
<b>Mono Input</b>	
Mic Input	electronically balanced, discrete input configuration
Bandwidth	10Hz to 60kHz $\pm$ 3dB
Distortion (THD & N)	0.01% at +4 dBu, 1kHz, Bandwidth 80 kHz
Mic E.I.N (22Hz-22kHz)	-129.5 dBu, 150 Ohm source -117.3 dBq, 150 Ohm source -132.0 dBu, input shorted -122.0 dBq, input shorted
TRIM range	+10dB to +60dB
Line Input	electronically balanced
Bandwidth	10 Hz to 60 kHz $\pm$ 3dB
Distortion (THD & N)	0.01% at +4 dBu, 1kHz, Bandwidth 80 kHz
Line level range	+10 dBu to -40 dBu
<b>Equalization</b>	
Hi Shelving	12 kHz +/- 15dB
Mid Range	2.5 kHz +/- 15dB
Lo Shelving	80 Hz +/- 15dB
<b>Master Mix section</b>	
Max Output	+22 dBu balanced
Aux Send Max Out	+22 dBu unbalanced
Control Room Out	+22 dBu unbalanced
Signal-To-Noise Ratio	112 dB, all channels at Unity Gain
<b>Power supply</b>	
Mains Voltages	U.K / Australia / Malaysia ~ 240 V AC, 50 Hz